

PRODUCT DATASHEET

SMART+ WIFI Multipower Socket EU White

SMART+ WIFI Multipower Socket GEN2 | Multi Power Socket with smart 4 EU sockets and USB ports with WiFi technology



Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems
- USB ports available for power supply

Product benefits

- Smart Multi power socket: Simple connection of electric devices via smart sockets and smart USB ports
- Monitors energy usage of connected devices and tracks the energy consumption
- Integrates conventional electric equipment into compatible smart home systems
- Enables switching of conventional light sources and other electric devices
- Wireless control via app or voice control

Product features


- Smart 4 standard sockets and smart 4 USB ports for charging (2 ports each Type A and C)
- USB charger: Fast charging with USB Power Delivery (USB PD) up to 20W power
- Power sockets can be controlled individually and USB ports are controlled as one group
- High switching power: up to 3,680 W / 16 A
- Energy meter
- Scheduling
- 1.5 m power cable for flexible installation
- Network protocol: WiFi (2.4 GHz)
- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0)
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Controllable via SMART+ WiFi Remote Controller

TECHNICAL DATA

Electrical data

Nominal voltage	230 V
Nominal current	16 A
Mains frequency	50 Hz

Dimensions & Weight



Product weight	586.00 g
Length	315 mm
Width	62 mm
Height	40 mm

Lifespan

Number of switching cycles	10000
----------------------------	-------

Colors & materials

Product color	White
---------------	-------

Temperatures & operating conditions

Ambient temperature range	-5...+40 °C
---------------------------	-------------

Capabilities

Type of connection	Plug
Compatible smart home technology	Amazon Alexa / Google Home

Certificates & Standards

Standards	CE
Protection class	I
Type of protection	IP20

Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Multi Power Socket, after use in order to avoid them being accidentally switched on.

- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Multi Power Socket in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (for max. 16 A)
- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.

DOWNLOAD DATA

Documents and certificates		Document name
	User instruction / safety instructions	SMART+ MULTIPOWER SOCKET
	Addon technical information	Wifi remote control compatibility list
	Addon technical information	Wifi remote control compatibility list (DE)
	Legal information	Safety insert G11234413
	Declarations of conformity	SMART WIFI MULTIPOWER SOCKET EU
	EU Data Act	SMART WiFi Plugs

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854418198	Folding box 1	76 mm x 76 mm x 377 mm	633.00 g	2.18 dm ³
4099854418204	Shipping box 4	390 mm x 165 mm x 165 mm	2764.00 g	10.62 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

- Further information and frequently asked questions (FAQs) at www.ledvance.com/en-int/home-lighting/services/faq

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.